

	GoLive	Spark I	Spark II	UV100	UV100Pro	UV600	UV800
Max Number Connections	2	9	10	9	10	10	10
Internal Modems	1	3	4	3	4	6	6
4G Version	Smartphone	3	4	3	4	6	6
5G/4G Version	Smartphone	1+2	1+3	1+2	1+3	3+3	3+3
USB Ports	0	4	4	4	4	2	2
WiFi	1	1	1	1	1	1	1
LAN	-	1	1	1	1	1	1
H.264	Yes	Yes	Yes	Yes	Yes	Yes	Yes
HEVC	Yes	Yes	Yes	Yes	Yes	Yes	Yes
4:2:0/4:2:2	4:2:0	4:2:0	4:2:0	4:2:0	4:2:0	4:2:0	4:2:0/4:2:2
8/10 bits	8	8	8	8	8	8	8/10
Max Bitrate (Mbps)	15	15	15	25	35	50	70
SDI Input	-	1	1	1	1	1	1
3G/12G Support	-	3G	3G	3G	3G	3G	12G
Up to	1080p30	1080p60	1080p60	1080p60	1080p60	1080p60	2160p60
HDMI Input	-	1	1	1	1	1	1
1.4/2.0 Support	-	1.4	1.4	1.4	1.4	1.4	2
Up to	2160p30	1080p60	1080p60	1080p60	1080p60	2160p30	2160p60
Embedded Audio Channels	1	2	4	2	4	8	2
Analog Audio Inputs	1	-	2	-	2	2	-
Bidirectional Intercom	No	Yes	Yes	Yes	Yes	Yes	Yes
Video/Audio Return	No	No	No	No	No	Yes	Yes
Tally	No	Yes	Yes	Yes	Yes	Yes	Yes
Display (inches)	Smartphone	3"	3"	3"	4"	5"	5"
Internal Battery Life (hs)	Smartphone	+2hs	+2hs	+2hs	+2hs	+4hs	+4hs
Power Supply - Battery Charger	Smartphone	Standard	Standard	Standard	Standard	Standard	Standard
Beltpack	-	Standard	Standard	Standard	-	-	-
Backpack	-	Option	Option	Option	Standard	Standard	Standard